

## Analog Way Seamless Switcher 2012

	optional												
Typ	DiVentix II VO	Eikos	Eikos LE	Opus	Opus LE	SmartEdge	SmartQuad	Smart Matrix	Smart Matrix LE	Pulse	Pulse LE	SmartVu	SmartVu LE
	DVX8044	EKS500	EKS400	OPS300	OPS200	STE100	SQD200	SMX200	SMX100	PLS300	PLS200	SVU300	SVU200
Listenpreis	22.050 €	15.990 €	12.990 €	10.490 €	6.990 €	5.990 €	7.290 €	9.990 €	5.990 €	5.990 €	4.990 €	4.490 €	3.590 €
<b>Betriebsarten</b>													
Mixer	x	x	x	x	x					x	x	x	x
Matrix	x	x	x	x				x	x				
Embedded Softedge	x					x							
Quadravision		x					x						
Mosaik		x	x										
<b>Layer pro Main Output</b>													
Live	4 / 1 in Matrix	3 / 2 in Matrix	3 / 2 in Matrix	3 / 1 in Matrix	3	1	4	2	1	2	2	2	1
Frame	1	1	1	1	1	0	1	1	0	1	0	0 (1)	0
Logo	2	2	2	2	2	0	1	1	0	1	0	0 (1)	0
<b>Eingänge</b>													
	8	12	12	12	11	10	11	12	10	10	10	7	5
Analog universal	8	6	6	7 + 1 Front	7	6	7	6	6	6	6	4	4
DVI skaliert	4	2	2	2	2	2	2	2	2	2	2	1	1
SD-HD-SDI	4	4	4	2	2	2	2	4	2	2	2	2	0
Max. Auflösung	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA
Audio	0 (8)	8 + emb. SDI	8 + emb. SDI	10 + emb. SDI	9 + emb. SDI	6 + emb. SDI	10 + emb. SDI	9 + emb. SDI	8 + emb. SDI	6 + emb. SDI	6 + emb. SDI	5 + emb. SDI	5
Symmetrisch / unsymmetrisch	0 (8 sym.)	8 sym.	8 sym.	9 unsym. + 1 sym.	8 unsym. + 1 sym.	6 unsym. / 1 sym.	8 unsym. / 2 sym.	8 sym.	6 unsym.	6 unsym. / 1 sym.	6 unsym.	5 unsym.	5 unsym.
Aux. Audioeingang	0 (sym.)	sym.	sym.	sym.	sym.	sym.	sym.	sym.	sym.	sym.	sym.	sym.	sym.
HDCP-Kompatibel	x	x	x	x	x	x	x	x	x	x	x	x	x
<b>Ausgänge</b>													
Main	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15
Max. Auflösung	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA	2K / WUXGA
Preview / Main 2	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	1xDVI-I + 1xHD15	0
separater Videoausgang	x (Breakoutkabel)	x	x	x (Breakoutkabel)	0	0	x (Breakoutkabel)	x	0	0	0	0	0
Videoausgang FBAS + Y/C	x	x	x	x	0	0	x	x	0	0	0	0	0
Videoausgang RGB/YUV	x	x	x	x	0	0	x	x	0	0	0	0	0
Videoausgang SD/HDSDI	x	x	x	x	0	0	x	x	0	0	0	0	0
Videoausgang DVI	x	0	0	0	0	0	0	0	0	0	0	0	0
Audio Symmetrisch / unsymmetrisch	0 (2 sym.)	2 sym. / 1 SDI emb.	2 sym. / 1 SDI emb.	2 sym. / 1 SDI emb.	2 sym.	1 sym.	2 sym.	2 sym.	1 sym.	1 sym.	1 sym.	1 sym.	1 sym.
HDCP-Kompatibel	x	x	x	x	x	x	x	x	x	x	x	x	x
<b>Funktionen</b>													
Clean Cut	0	x	x	x	x	x	x	x	x	x	x	x	x
Cut	x	x	x	x	x	x	x	x	x	x	x	x	x
Fade	x	x	x	x	x	x	x	x	x	x	x	x	x
Wipe	0	x	x	x	x	x	x	x	x	x	0	x	0
Wipe von innen	0	x	x	x	x	x	x	x	x	x	0	x	0
Wipe von außen	0	x	x	x	x	x	x	x	x	x	0	x	0
Slide	x	x	x	x	x	x	x	x	x	x	0	x	0
Smooth Move	0	x	x	x	x	x	x	x	0	x	0	x	0
1x PiP auf Live (Mixer / Matrix)	x / o	x / x	x / o	x / o	x	0	x	x	0	x	x	x	0
1x PiP auf Frame (Mixer / Matrix)	x / o	x / x	x / x	x / o	x	0	x	x	0	x	0	0 (x)	0
2x PiP auf Live (Mixer / Matrix)	x / o	x / o	x / o	x / o	x / o	0	x	0	0	0	0	0	0
2x PiP auf Frame (Mixer / Matrix)	x / o	x / x	x / o	x / o	x / o	0	x	x	0	x	0	0	0
3x PiP auf Frame	x	x	x	erfordert Orchestra	erfordert Orchestra	0	x	0	0	0	0	0	0
3x PiP auf Live	x	o / x bei Quadrav.	0	0	0	0	x	0	0	0	0	0	0
4 x PiP auf Frame	x	o / x bei Quadrav.	0	0	0	0	x	0	0	0	0	0	0
Fliegendes PiP	x	x	x	x	x	0	x	x	0	x	x	x	0
Dynamisches PiP (Faden, Zoomen)	0	x	0	0	0	0	x	x	0	0	0	0	0
Matrix Mirror Mode	0	x	x	0	0	0	0	x	0	0	0	0	0
Chroma/Luma key	x	x	x	x	x	x	x	x	x	x	x	x	0
Preview-Ausgang (Skaliert)	x	x	x	x	x	0	x	0	0	x	x	(x)	0
Logo & Frame Speicher	8 Logos / 8 Frames	8 Logos / 8 Frames	8 Logos / 8 Frames	8 Logos / 8 Frames	7 Logos / 7 Frames	0	7 Logos / 7 Frames	8 Logos / 8 Frames	0	6 Logos / 6 Frames	0	(490€, 4 Logos/4Frames)	0
Memory Preset	8	8	8	4	4	4	4	4	4	4	4	4	0
Interne Testbilder	x	x	x	x	x	x	x	x	x	x	x	x	x
Audio Breakaway	0 (x)	x	x	x	x	x	x	x	x	x	x	x	x
Audio Delay Compensation	0	x	x	x	x	x	x	0	0	x	x	x	x
<b>Bedienung</b>													
T-Bar auf Frontpanel	0	0	0	x	0	0	0	0	0	0	0	0	0
Display am Frontpanel	4-zeilig	4-zeilig	4-zeilig	4-zeilig	4-zeilig	2-zeilig	4-zeilig	4-zeilig	2-zeilig	2-zeilig	2-zeilig	2-zeilig	2-zeilig
RS232 / LAN	x	x	x	x	x	x	x	x	x	x	x	x	x
Projektorsteuerung (RS-232)	0	x	x	x	x	x	x	x	x	x	x	x	x
Gehäuse	3HE	2HE	2HE	2HE	2HE	1HE	2HE	2HE	1HE	1HE	1HE	1HE	1HE
Bedienkonsole RK300	0	x	x	x	x	x	x	x	x	x	x	x	x
Bedienkonsole TRK800	0	x	x	x	x	x	x	x	x	x	x	x	x
Bedienkonsole Orchestra	x	x	x	x	x	x	x	x	x	x	x	x	x
Bedienkonsole Axion 2	x	x	x	x	x	x	x	x	x	x	x	x	x